

Belfone BF-TM8500 VHF & UHF Mobile Radio

DMR Digital FM Transceiver



Always On Display:

Channel Name

Zone

TX: Frequency

RX: Frequency

RED: TRANSMIT (or TX)
 GREEN: RECEIVE (or RX)

NEVER connect non-specified microphones. The pin assignments may be different and the transceiver may be damaged.

4 F3 : -10 Channels **Programmable Key**

Jump backward by 10 channels.

5 F4 : +10 Channels/Back **Programmable Key**

Jump forward by 10 channels.

Also functions as a “back” button when in menu.

6 Orange Key **Programmable Key**

When supported, this can be programmed as an emergency or SOS button (contact us for details).

Currently inactive. But, if supported, short press to enable emergency feature or long press to disable.

7 D-Pad : Volume/Channel/Navigation

- **Left Key** - Short press to select a channel downwards, long press to select zone
- **Right Key** - Short press to select a channel upwards, long press to select zone
- **Up Key** - Short press to increase volume
- **Down Key** - Short press to decrease volume.

8 OK Key : Confirmation/Menu

Press to confirm or go to menu.

1 Power : Switch key

Short press (1 second) to power on the radio. Long press till you hear a beep to turn off the radio.

2 F1 : Zone Selection **Programmable Key**

Push the button, then use the “up” & “down” buttons on the D-Pad to select required zone.

3 F2 : Zone Selection **Programmable Key**

Push the button, then use the “up” & “down” buttons on the D-Pad to select required zone.

F2 key has been programmed to function the same as the F1 key (contact us if you have questions).



**Scan to
download
brochure**

Got Questions? Contact us!

Since 1993, we've specialized in programming, repairing, and installing mobile two-way radios similar to yours. If you have any questions or need further assistance, don't hesitate to reach out to us. We're here to help.

(780) 539-3962

customerservice@expertmobile.ca

expertmobile.ca